

SparkFun SerLCD 4 lines 20 character wide placing text help

Serial.write(0xFE); Serial.write(0x80+HEX);		Column																				
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	
Row	1																					Text
		0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	DEC
		0x00	0x01	0x02	0x03	0x04	0x05	0x06	0x07	0x08	0x09	0x0A	0x0B	0x0C	0x0D	0x0E	0x0F	0x10	0x11	0x12	0x13	HEX
	2																					Text
		64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	DEC
		0x40	0x41	0x42	0x43	0x44	0x45	0x46	0x47	0x48	0x49	0x4A	0x4B	0x4C	0x4D	0x4E	0x4F	0x50	0x51	0x52	0x53	HEX
	3																					Text
		20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	DEC
		0x14	0x15	0x16	0x17	0x18	0x19	0x1A	0x1B	0x1C	0x1D	0x1E	0x1F	0x20	0x21	0x22	0x23	0x24	0x25	0x26	0x27	HEX
	4																					Text
		84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100	101	102	103	DEC
		0x54	0x55	0x56	0x57	0x58	0x59	0x5A	0x5B	0x5C	0x5D	0x5E	0x5F	0x60	0x61	0x62	0x63	0x64	0x65	0x66	0x67	HEX